



Download

DXF 2D 616_7_8_9.dxf Montaggi • 614-5-6-7-8-9_safety.pdf • safety1.dxf • safety2.dxf



616 Safety permanent 1 hr emergency S.E.

Housing: Vandal-resistant, self-extinguishing, UV-stabilized, anti-yellowing grey polycarbonate, . Diffuser: Vandal resistant, V2 self-extinguishing, UV-stabilised clear

polycarbonate, anti-glare frosted inside; smooth, dust-proof outside Reflector: Reflecting white polycarbonate. Lampholder: Polycarbonate with phosphorous bronze contacts

Electric gear: -230V-240/60Hz power supply with electronic ballast. Hard wire, cross-section 0.50 sqmm, and high-temperature resistant (up to 90°C) PVC-HT sheath, in accordance with CEI 20-20 standards. 2P terminal block (maximum allowed lead cross-section 2.5 sqmm.).

Èquipment: Rubber cable gland ø 1/2 inch gas thread (min cable ø 9, max ø 12 mm) to maintain IP65 protection. Standard inspection LED

12 mm) to maintain IP65 protection. Standard inspection LED Regulations: Manufactured in compliance with EN60598 - CEI 34 -21 standards. The level of protection complies with the EN60529 standard. S.E. Emergency (Only emergency): In the event of a black-out the one lamp connected to the back-up circuit stays on, thus avoiding the inconvenience caused by a sudden absence of all light. Emergency run time: 60 minutes. When power is restored, the battery

recharges automatically in 12 hours.

On request: with troubleshooting (sub-code -0066).

Code	Gear	Kg	Lumen-K-CRI	

74

Code	Gear	Kg	Lumen-K-CRI	WTot	Base	Colour
112531-0066	CEM-L	0.83	FLC 1x11S/E-900lm-4000k-Ra 1b	0 W	2G7	GREY
112532-0066	CEM-L	0.96	FLC 1x18L-1200Im-4000K-Ra 1b	0 W	2G11	GREY
112531-00	CEM-L	0.83	FLC 1x11S/E-900lm-4000k-Ra 1b	0 W	2G7	GREY
112530-0066	CEM-L	0.88	FL 8-430lm-4000K-Ra 1b	0 W	G13	GREY
112530-00	CEM-L	0.86	FL 8-430lm-4000K-Ra 1b	0 W	G13	GREY
112532-00	CEM-L	0.94	FLC 1x18L-1200Im-4000K-Ra 1b	0 W	2G11	GREY



322 Baffle plate for asymmetry

356

The reported luminous flux is the flux emitted by the light source with a tolerance of ± 10% compared to the indicated value. The W tot column indicates the total wattage absorbed by the system without exceeding 10% of the indicated