

Adequate lighting ensures proper perception of the environment and enables us to feel comfortable with our surroundings. This is the concept underlying the creation of the Milano recessed floodlight, ideal for quick, low-cost installation

in any exhibition setting and fulfil interior decorators' artificial lighting

Lampholder: Ceramic with silver-plated contacts, or polycarbonate with

Electric gear: 230V/50Hz power supply, with thermal protection for discharge lamps. Flexible silicone insulated wire terminated with admiralty brass clamps, with fibreglass braid, cross-section: 1.5 sqmm. 2P+T terminal block (with plug-

Standard supply: Includes adjustable steel bracket. Hinge opening of the glass holding ring for easier maintenance. Regulations: Manufactured in accordance with standards EN60598 – CEI 34

-21. Degree of protection in accordance with standards EN60529.

Reflector: wide-beam; oxidised and polished aluminium.

Diffuser: Tempered glass protection shield.



Download DXF 2D - 81011.dxf

Montaggi - 771810 milano.pdf







Code	Gear	Kg	Lumen-K-CRI	WTot	Base	Colour
22081177-0885	CELL	1.30	CDM-TS 150-13250lm-3000K-Ra 1b	161 W	Rx7s	SILVER
22081011-08	CELL	1.05	JM-TS 70 excellence-6200lm-3000K-Ra 1b	86 W	Rx7s	WHITE
22081115-0885	CELL	1.30	CDM-TS 150-13250lm-3000K-Ra 1b	161 W	Rx7s	WHITE
22081073-0885	CELL	1.05	CDM-TS 70-6500lm-3000K-Ra 82	78 W	Rx7s	SILVER
22081073-08	CELL	1.05	JM-TS 70 excellence-6200lm-3000K-Ra 1b	86 W	Rx7s	SILVER
22081177-08	CELL	1.30	JM-TS 150 excellence-12000lm-3000K-Ra 1b	161 W	Rx7s	SILVER
22081115-08	CELL	1.30	JM-TS 150 excellence-12000lm-3000K-Ra 1b	161 W	Rx7s	WHITE
22081011-0885	CELL	1.05	CDM-TS 70-6500lm-3000K-Ra 82	78 W	Rx7s	WHITE
22081013-00	CELL	1.15	CMH-TS 35-3400lm-3000K-Ra 2a	56 W	Rx7s	WHITE
		•				•

Milano "TS" wide beam

Housing: Made of steel sheet.

phosphor bronze contacts.

Lamps: Discharge lamps included.

Use with control gear box 92060/65 or 92011/21.

socket connector).

requirements.

Accessories





The reported luminous flux is the flux emitted by the light source with a tolerance of ± 10% compared to the indicated value. The W tot column indicates the total wattage absorbed by the system without exceeding 10% of the indicated