




Download DXF 2D - 1141smp.dxf

Montaggi - 1141\_sempione.pdf





## For roads, shop-lined and private - 1141 Sempione

Housing: In die-cast aluminium.

Reflector: In anodized, polished, pressed 99.85 aluminium, 6/8  $\mu$  thick, with flux recovery system.

Cover: Hinge-opening, vandal resistant and self-extinguishing polycarbonate, UV-stabilized.

Diffuser: In vandal resistant and V2 self-extinguishing polycarbonate, UVstabilized. With latches.

Painting: With polyester fluid, grey, RAL 7035, upon chromate treatment, resistant to corrosion.

Lampholder: In ceramics, with silver-plated contacts. Socket E27; E40

Electric gear: 230 V/50 Hz power supply. Silicone wire terminated with quickconnect clamps in admiralty brass. 2P+T nylon terminal block with maximum allowed lead cross-section of 4 sqmm.

Equipment: Silicone rubber gasket. Equipped with an anti-condensation filter. Lamp focus can be axial adjusted. Mast-top (Ø 60/76) or mast-arm (Ø 42/60) mounting. During maintenance the housing and diffuser remain attached for easy maintenance.

Standards: Produced according to applicable EN60598-1 CEI 34-21 standards, IP54IK08 degree of protection for lamp housing and IP43IK08 for electric gear box according to EN 60529 standards. Wind surface: 1479 sqcm.

Non-polluting louvre, ideal for installation in zone 1 (UNI10819), with suitable inclination.

Gear	Kg	Lumen-K-CRI	WTot	Base	Colour
CNR	6.66	SAP-T 150-17200lm-2000K-Ra 4	166 W	E40	GREY
CNR	6.66	SAP-T 150-17200lm-2000K-Ra 4	157 W	E40	GREY
CNR	6.66	SAP-T 150-17200lm-2000K-Ra 4	169 W	E40	GREY
CNR	6.66	SAP-T 100-9000lm-2000K-Ra 4	114 W	E40	GREY
CNR	6.66	SAP-T 100-9000lm-2000K-Ra 4	114 W	E40	GREY
CNR	8.26	SAP-T 250-33000lm-2000 K-Ra 4	277 W	E40	GREY
CNR	8.26	SAP-T 250-33000lm-2000 K-Ra 4	277 W	E40	GREY
CNR	8.26	SAP-T 250-33000Im-2000 K-Ra 4	277 W	E40	GREY
	CNR CNR CNR CNR CNR CNR CNR CNR	CNR 6.66   CNR 6.66   CNR 6.66   CNR 6.66   CNR 6.66   CNR 6.26   CNR 8.26   CNR 8.26	CNR 6.66 SAP-T 150-17200Im-2000K-Ra 4   CNR 6.66 SAP-T 100-9000Im-2000K-Ra 4   CNR 6.66 SAP-T 100-9000Im-2000K-Ra 4   CNR 6.66 SAP-T 100-9000Im-2000K-Ra 4   CNR 8.26 SAP-T 250-33000Im-2000 K-Ra 4   CNR 8.26 SAP-T 250-33000Im-2000 K-Ra 4	CNR 6.66 SAP-T 150-17200Im-2000K-Ra 4 166 W   CNR 6.66 SAP-T 150-17200Im-2000K-Ra 4 157 W   CNR 6.66 SAP-T 150-17200Im-2000K-Ra 4 169 W   CNR 6.66 SAP-T 150-17200Im-2000K-Ra 4 169 W   CNR 6.66 SAP-T 100-9000Im-2000K-Ra 4 114 W   CNR 6.66 SAP-T 100-9000Im-2000K-Ra 4 114 W   CNR 6.66 SAP-T 100-9000Im-2000K-Ra 4 114 W   CNR 8.26 SAP-T 250-33000Im-2000 K-Ra 4 277 W   CNR 8.26 SAP-T 250-33000Im-2000 K-Ra 4 277 W	CNR 6.66 SAP-T 150-17200Im-2000K-Ra 4 166 W E40   CNR 6.66 SAP-T 150-17200Im-2000K-Ra 4 157 W E40   CNR 6.66 SAP-T 150-17200Im-2000K-Ra 4 169 W E40   CNR 6.66 SAP-T 150-17200Im-2000K-Ra 4 169 W E40   CNR 6.66 SAP-T 100-9000Im-2000K-Ra 4 114 W E40   CNR 6.66 SAP-T 100-9000Im-2000K-Ra 4 114 W E40   CNR 6.66 SAP-T 100-9000Im-2000K-Ra 4 114 W E40   CNR 8.26 SAP-T 250-33000Im-2000 K-Ra 4 277 W E40   CNR 8.26 SAP-T 250-33000Im-2000 K-Ra 4 277 W E40

Accessorie





- 74 double pole mount

- 48 wall barcket

1.

- 72 wall mount

The reported luminous flux is the flux emitted by the light source with a tolerance of  $\pm$  10% compared to the indicated value. The W tot column indicates the total wattage absorbed by the system without exceeding 10% of the indicated