



Download DXF 2D - 1733c.dxf 3DS - disano\_1733\_faro\_4.3ds 3DM disano\_1733\_faro\_4.3dm Montaggi - faro\_faro3\_faro4\_tn.pdf



## 1733 Faro 4 - short version special

Housing: In extruded aluminium, cylindrical section, Ø 180. Diffuser: In vandal resistant and V2 self-extinguishing clear polycarbonate, UVstabilized.

Painting: the standard liquid immersion coating consists of a first metal surface pre-treatment stage, a successive epoxy cataphoresis corrosion and salt resistant coating, and a final layer of bi-component acrylic liquid UV-stabilised coating.

Lampholder: In white polycarbonate, with phosphor bronze contacts (FLC), socket G24q In ceramics with silver-plated contacts. Socket E27.

Electric gear: 230-240V/50Hz power supply. Hard wire, 0.50 sqmm cross-section, PVC-HT sheath resistant up to 90°C, according to CEI 20-20 standard, or silicone flexible wire terminated with quick-connect clamps in admiralty brass, glass braid, 1.0 sqmm cross-section. 2P+T terminal block, maximum allowed lead cross-section of 4 sqmm. Standard supply: With base and anchor bolts to bury. Supplied with socket-pin

connector for quick installation and air recycle valve Regulations: Produced according to applicable EN60598-1 CEI 34-21 standards, IP64IK10 degree of protection in compliance with EN 60529 standards.

Non-polluting louvre, ideal for installation in zone 1 (UNI10819).



Gear	Kg	Lumen-K-CRI	WTot	Base	Colour
CNR-L	4,22	JM-E 70-5300Im-4000k-Ra 1b	82 W	E27	GRAPHITE
CELL	4,11	FLC 1x26T-1800lm-4000K-Ra 1b	27 W	G24d-3	GRAPHITE
CNR-L	4,22	SAP-T 70-6000lm-2000K-Ra 4	83 W	E27	GRAPHITE
	CNR-L CELL	CNR-L 4,22   CELL 4,11	CNR-L 4,22 JM-E 70-5300Im-4000k-Ra 1b   CELL 4,11 FLC 1x26T-1800Im-4000K-Ra 1b	CNR-L 4,22 JM-E 70-5300lm-4000k-Ra 1b 82 W   CELL 4,11 FLC 1x26T-1800lm-4000K-Ra 1b 27 W	CNR-L 4,22 JM-E 70-5300lm-4000k-Ra 1b 82 W E27   CELL 4,11 FLC 1x26T-1800lm-4000K-Ra 1b 27 W G24d-3

## sori



399 Connector for solid line

The reported luminous flux is the flux emitted by the light source with a tolerance of ± 10% compared to the indicated value. The W tot column indicates the total wattage absorbed by the system without exceeding 10% of the indicated